

## 136-960 MHz Quarterwave

## FLEXIBLE MOBILE ANTENNA

**Performance:** These antennas provide unity gain in an extremely flexible whip design for standard duty service. They have a power handling capacity of 200 watts.

**Stylish and Durable:** These antennas manufactured using the finest corrosion resistant materials and finishes available.

**Economical:** These antennas provide an outstanding price to performance ratio.

**Versatile:** These antennas are shipped with a 20" whip that can be cut to a specific frequency range between 136 and 960MHz. The cap can be removed and replaced after cutting. A frequency cutting chart is supplied.

**Standard Mounting:** This series of antennas mate with the standard TAD/NMO type mount, providing an excellent moisture seal even when the antenna is removed.

**ELECTRICAL SPECIFICATIONS:**

**FREQUENCY RANGE:** 136-960MHz  
**GAIN:** Unity  
**IMPEDANCE:** 50 ohms  
**POWER RATING:** 200 watts  
**VSWR:** <1.5:1

**MECHANICAL SPECIFICATIONS:**

**RADIATOR:** Nickel Titanium  
**BASE:** Brass, triple plated chrome nut  
**LENGTH:** Frequency dependent 20" max.  
**MOUNTING:** Standard TAD/NMO type

**Vertical Pattern**